




PCT / IB 03 / 02673
12.06.03



INVESTOR IN PEOPLE

The Patent Office
Concept House
Cardiff Road
Newport
South Wales
NP10 8QQ



I, the undersigned, being an officer duly authorised in accordance with Section 74(1) and (4) of the Deregulation & Contracting Out Act 1994, to sign and issue certificates on behalf of the Comptroller-General, hereby certify that annexed hereto is a true copy of the documents as originally filed in connection with the patent application identified therein.

In accordance with the Patents (Companies Re-registration) Rules 1982, if a company named in this certificate and any accompanying documents has re-registered under the Companies Act 1980 with the same name as that with which it was registered immediately before re-registration save for the substitution as, or inclusion as, the last part of the name of the words "public limited company" or their equivalents in Welsh, references to the name of the company in this certificate and any accompanying documents shall be treated as references to the name with which it is so re-registered.

In accordance with the rules, the words "public limited company" may be replaced by p.l.c., plc, P.L.C. or PLC.

Re-registration under the Companies Act does not constitute a new legal entity but merely subjects the company to certain additional company law rules.

**PRIORITY
DOCUMENT**


SUBMITTED OR TRANSMITTED IN
COMPLIANCE WITH RULE 17.1(a) OR (b)

Signed

Dated

14 March 2003

BEST AVAILABLE COPY



Patents Form 1/77

Patents Act 1977
(Rule 16)

THE PATENT OFFICE

27 JUN 2002

RECEIVED BY FAX

The
Patent
Office

1/77

27JUN02 E729177-1 002879
P01/7700 0.00-0214879.9

Request for grant of a patent
(See notes on the back of this form. You can also get an explanatory leaflet from the Patent Office to help you fill in this form)

The Patent Office

Cardiff Road
Newport
Gwent NP10 8QQ

1. Your reference	PHGB 020104		
2. Patent application number (The Patent Office will fill in this part)	0214879.9		27 JUN 2002
3. Full name, address and postcode of the or of each applicant (underline all surnames)	KONINKLIJKE PHILIPS ELECTRONICS N.V. GROENEWOUDSEWEG 1 5621 BA EINDHOVEN THE NETHERLANDS.		
Patents ADP Number (if you know it)	7419294001		
If the applicant is a corporate body, give the country/state of its incorporation	THE NETHERLANDS		
4. Title of the invention	COMMUNICATION SYSTEM		
5. Name of your agent (if you have one)	KEVIN JAMES SCOTT		
"Address for service" in the United Kingdom to which all correspondence should be sent (including the postcode)	Philips Intellectual Property & Standards Cross Oak Lane Redhill Surrey RH1 5HA		
Patents ADP number (if you know it)	7688914002		
6. If you are declaring priority from one or more earlier parent applications, give the country and the date of filing of the or of each of these earlier applications and (if you know it) the or each application number	Country	Priority Application number	Date of filing
7. If this application is divided or otherwise derived from an earlier UK application, give the number and the filing date of the earlier application	Number of earlier application		Date of filing (day/month/year)
8. Is a statement of inventorship and of right to grant of a patent required in support of this request? (Answer "Yes" if: a) any applicant named in part 3 is not an inventor, or b) there is an inventor who is not named as an applicant, or c) any named applicant is a corporate body. See note (d))	YES		

Patents form

Patents Form 1/77

- Enter the number of sheets for any of the following items you are filing with this form.
Do not count copies of the same document.

Continuation sheets of this form

Description

12

Claims(s)

4

Abstract

1

Drawings

3

10. If you are also filing any of the following, state how many against each item:

Priority Documents

Translations of priority documents

Statement of inventorship and right

to grant of a patent (*Patents Form 7/77*)

Request for preliminary examination and

search (*Patents Form 9/77*)

Request for substantive examination

(*Patents Form 10/77*)

Any other documents

(*Please specify*)

11. I/We request the grant of a patent on the basis of this application.

Signature

Date

27 June 2002

12. Name and daytime telephone number of person to contact in the United Kingdom

01293 81 5281

K J SCOTT

Warning

After an application for a patent has been filed, the Comptroller of the Patent Office will consider whether publication or communication of the invention should be prohibited or restricted under Section 22 of the Patents Act 1977. You will be informed if it is necessary to prohibit or restrict your invention in this way. Furthermore, if you live in the United Kingdom, Section 23 of the Patents Act 1977 stops you from applying for a patent abroad without first getting written permission from the Patent Office unless an application has been filed at least 6 weeks beforehand in the United Kingdom for a patent for the same invention and either no direction prohibiting publication or communication has been given, or any such direction has been revoked.

Notes

- If you need help to fill in this form or you have any questions, please contact the Patent Office on 0645 500505.
- Write your answers in capital letters using black ink or you may type them.
- If there is not enough space for all the relevant details on any part of this form, please continue on a separate sheet of paper and write "see continuation sheet" in the relevant part(s). Any continuation sheet should be attached to this form.
- If you have answered "Yes" *Patents Form 7/77* will need to be filed.
- Once you have filled in the form you must remember to sign and date it.
- For details of the fee and ways to pay please contact the Patent Office.

DESCRIPTION

COMMUNICATION SYSTEM

5 The present invention relates to a communication system and further relates to primary and secondary stations for use in such a system and to a method of operating such a system. While the present specification describes a system with particular reference to the Universal Mobile Telecommunication System (UMTS), it is to be understood that such techniques are equally
10 applicable to use in other communication systems.

 There is a growing demand in the mobile communication area for a system having the ability to download large blocks of data to a Mobile Station (MS) on demand at a reasonable rate. Such data could for example be web
15 pages from the Internet, possibly including video clips or similar. Typically a particular MS will only require such data intermittently, so fixed bandwidth dedicated links are not appropriate. To meet this requirement in UMTS, a High-Speed Downlink Packet Access (HSDPA) scheme is being developed which may facilitate transfer of packet data to a mobile station at up to at least
20 4Mbps.

 In currently proposed embodiments of HSDPA, the MS signals regular measurements of the downlink channel quality (known as Channel Quality Information, CQI) to the serving Base Station (BS). The reported CQI measurements take the form of a recommended transmission format which the
25 MS believes would result in successful transmission of a downlink packet in the prevailing channel characteristics. A change of 1dB in measured channel quality will typically result in a change in the recommended transmission format.

 The BS signals the frequency of CQI reporting to the MS as a
30 parameter, with the maximum frequency being once per Transmission Time Interval (TTI), which in the case of HSDPA is 3 slots. In some currently

proposed HSDPA embodiments, the frequency of CQI reporting may be varied on a semi-static basis depending on the level of downlink packet activity.

On receiving CQI reports from the mobile stations actively using HSDPA in its cell, the BS scheduler must decide which mobiles will be
5 scheduled for transmission of a packet and with what MCS (Modulation and Coding Scheme). There will be a minimum delay of around 6 slots between the
~~end of the mobile's measurement and the downlink packet transmission using~~
the corresponding MCS. If the CQI reporting frequency is lower than once per
TTI, the mean delay between the mobile's measurement and downlink packet
10 transmission will be greater.

During this delay the channel conditions may change, resulting in an increased probability that transmission of the packet will fail and hence that the packet will need to be retransmitted. This therefore reduces the total downlink
throughput and increases the delay between data arriving at the BS and being
15 successfully received by the MS. The magnitude of the error between the
actual channel conditions at the time of packet transmission and the reported
CQI increases as the MS speed increases.

One known way in which the BS can attempt to compensate for the change in channel conditions after the mobile's measurement is to adjust the
20 (implicit) data in the CQI report by the sum of downlink transmission power changes made under the closed-loop power control mechanism (of a parallel downlink control channel), which operates at an update rate of 1500Hz.

Thus, if the net change in transmit power on the other downlink channels to a MS was +3dB, for example, since the mobile's measurement
25 report, the BS would schedule the packet transmission to that MS using an MCS corresponding to channel conditions 3dB worse than those reported by the MS. However, when the MS is moving at high speed the closed-loop power control does not operate fast enough to track the fades in the channel, as the channel becomes decorrelated from one slot to the next. In such
30 circumstances, the BS cannot use the power control commands received from the MS to correct reliably the CQI reports.

An object of the present invention is to address the problem of reduced throughput in the presence of changing channel conditions.

According to a first aspect of the present invention there is provided a
5 communication system having a downlink data channel for the transmission of data packets from a primary station to a secondary station and uplink and downlink control channels for the transmission of control information between the primary and secondary stations, wherein the secondary station has means for measuring at least one characteristic of the data channel and for
10 transmission of reports relating to one or more of the measured channel characteristics to the primary station on the uplink control channel, wherein the primary station has time signalling means for instructing the secondary station, via the downlink control channel, of the length of time during which channel measurements used to generate each report should be made and wherein the
15 primary station has means for determining at least one operational parameter of the data channel depending on the reports.

By enabling the measurements made by the secondary station to be averaged over different periods, total system throughput may be increased. In addition, suitable choices of averaging period enable the frequency of reports
20 to be reduced, thereby reducing general interference levels without reducing system performance. The averaging period may be varied depending on the speed of the secondary station, for example, this variation being initiated by either the primary or the secondary station.

According to a second aspect of the present invention there is provided
25 a primary station for use in a communication system having a downlink data channel for the transmission of data packets from the primary station to a secondary station and uplink and downlink control channels for the transmission of control information between the primary and secondary stations, wherein means are provided for receiving on the uplink control
30 channel reports relating to one or more measured channel characteristics of the data channel from the secondary station, time signalling means are provided for instructing the secondary station, via the downlink control

channel, of the length of time during which channel measurements used to generate each report should be made and means are provided for determining at least one operational parameter of the data channel depending on the reports.

5 According to a third aspect of the present invention there is provided a secondary station for use in a communication system having a downlink data channel for the transmission of data packets from a primary station to a
secondary station and uplink and downlink control channels for the
transmission of control information between the primary and secondary
10 stations, wherein means are provided for measuring at least one characteristic of the data channel, for transmission of reports relating to one or more of the measured channel characteristics to the primary station on the uplink control channel, and for receiving, via the downlink control channel, instructions of the
length of time during which channel measurements used to generate each
15 report should be made.

According to a fourth aspect of the present invention there is provided a secondary station for use in a communication system having a downlink data channel for the transmission of data packets from a primary station to a secondary station and uplink and downlink control channels for the
20 transmission of control information between the primary and secondary stations, wherein means are provided for measuring at least one characteristic of the data channel, for transmission of reports relating to one or more of the measured channel characteristics to the primary station on the uplink control channel, and for determining the length of time during which channel
25 measurements used to generate each report should be made.

According to a fifth aspect of the present invention there is provided a method of operating a communication system having a downlink data channel for the transmission of data packets from a primary station to a secondary station and uplink and downlink control channels for the transmission of control
30 information between the primary and secondary stations, wherein the secondary station measures at least one characteristic of the data channel and transmits reports relating to one or more of the measured channel

characteristics to the primary station on the uplink control channel, wherein the primary station instructs the secondary station, via the downlink control channel, of the length of time during which channel measurements used to generate each report should be made and wherein the primary station
5 determines at least one operational parameter of the data channel depending on the reports.

Embodiments of the present invention will now be described, by way of example, with reference to the accompanying drawings, wherein:

10 Figure 1 is a block schematic diagram of a radio communication system;

Figure 2 is a graph showing simulated delay (D) in seconds against offered load (O) in Mbps for a mobile moving at 10km/h, for a range of reporting rates, showing the effect of using power control information;

15 Figure 3 is a graph showing simulated delay (D) in seconds against offered load (O) in Mbps for a mobile moving at 120km/h, for a range of reporting rates, showing the effect of using power control information;

Figure 4 is a graph showing simulated delay (D) in seconds against offered load (O) in Mbps for a mobile moving at 120km/h, for a range of
20 reporting rates, showing the effect of averaging channel measurements;

Figure 5 is a graph showing simulated delay (D) in seconds against offered load (O) in Mbps for a mobile moving at 120km/h, with a reporting rate of once every 100 TTIs and a range of averaging periods; and

Figure 6 is a flow chart illustrating a method of operating a
25 communication system made in accordance with the present invention.

Referring to Figure 1, a radio communication system comprises a primary station (BS) 100 and a plurality of secondary stations (MS) 110. The BS 100 comprises a microcontroller (μ C) 102, transceiver means (Tx/Rx) 104
30 connected to antenna means 106, power control means (PC) 107 for altering the transmitted power level, and connection means 108 for connection to the PSTN or other suitable network. Each MS 110 comprises a microcontroller

(μ C) 112, transceiver means (Tx/Rx) 114 connected to antenna means 116, and power control means (PC) 118 for altering the transmitted power level. Communication from BS 100 to MS 110 takes place on a downlink channel 122, while communication from MS 110 to BS 100 takes place on an uplink channel 124.

Considering in particular a system including HSDPA functionality, the MS 110 makes regular measurements of characteristics of the downlink channel 122 which it reports to the BS 100 over the uplink channel 124, as discussed in the introductory section above. The channel characteristics would typically include one or more of bit error rate, signal to noise ratio, signal to interference level, etc. In a MIMO (Multiple Input Multiple Output) system they could also include separate characteristics for multiple antennas and multiple transmission paths.

It was indicated above that use of information from the closed-loop power control mechanism could be used by the BS 100 to compensate for changes in channel conditions after the measurement reported by the MS 110 was made. Simulations were performed to investigate this further. The following are the main assumptions made for the detailed specification of the simulated system:

- Hexagonal 19-cell layout, with a representative segment of the central cell considered for the throughput estimate.
- Number of stations 110 (per cell) = 12.
- Static TTI = 3 slots (2ms) = 1 sub-frame
- Propagation exponent = 3.76
- Single path Rayleigh fast fading model (flat spectrum)
- Channel conditions stationary during a sub-frame, derived from an average over the sub-frame
- Standard deviation of log-normal shadowing = 8dB
- Shadowing correlation between sites = 0.5
- 10% of BS power allocated to common pilot channel in all cells
- 30% of BS power allocated to common channels (including pilot) in all cells

- 70% of BS power allocated to HSDPA in all interfering cells
- 70% of BS power available to HSDPA in wanted cell
- Overheads due to dedicated channels associated with HSDPA not considered
- 5 • 10 spreading codes available for HSDPA
- MS capability: 5 spreading codes
- Spreading factor = 16
- Assumed available Modulation and Coding Schemes (MCS):
 1. QPSK 1/4 rate
 - 10 2. QPSK 1/2 rate
 3. QPSK 3/4 rate
 4. 16-QAM 1/2 rate
 5. 16-QAM 3/4 rate
- Equal transmission power per code
- 15 • Frame error rate computed from Signal to Interference Ratio (SIR) and block code performance bounds
- Scheduling delay = 2 slots (delay between BS decision on the schedule and start of data transmission)
- Channel quality data delay = 3 slots (delay between channel measurement
- 20 by MS 110 and reception of report by BS 100)

To represent streaming services it is assumed that the offered load is comprised of one constant rate data stream per MS 110. For simplicity equal bit rates are also assumed for each data stream. The data for each user is assumed to arrive at a queue in the BS 100, and the queue is updated every

25 TTI. It is assumed that one CRC (Cyclic Redundancy Check) is attached per packet.

As a default, Chase combining of re-transmissions is assumed. An erroneous packet is re-transmitted with the same MCS. Perfect maximum ratio combining is assumed, and the final SIR is computed as the sum of the SIRs

30 of the two packets to be combined. The maximum number of transmissions per packet is limited to 10.

8.

PHGB 020104

The reported CQI measurement is assumed to be in the form of a recommended MCS, with quantisation steps of 1dB between different recommendations. In total there are 30 quantisation levels, with the lowest corresponding to a CIR (Carrier to Interference Ratio) of -10dB (assuming all the BS power is allocated to HSDPA). The scheduler in the simulation chooses one of the available MCS based on the CQI value. The power control step size is assumed to be 1dB.

The simulated scheduler considers the following parameters:

- The MS 110 to which the most recent transmission was scheduled
- 10 • The CIR at the MS 110 (as determined by the BS 100)
- The long-term average CIR at the MS 110
- The amount of data in the queue at the BS 100
- The MS capability (e.g. the maximum number of channelisation codes that it can receive)

15 By default a proportional fair scheduler is used, which preferentially sends data to users with the highest value of $(\text{queue length}) \times (\text{instantaneous CIR})/(\text{average CIR})$.

Other general assumptions are that:

- A data packet for any user can be allocated to any channelisation code.
- 20 • More than one channelisation code can be allocated to one user.
- The code block size is equal to the amount of data that can be sent with one channelisation code, which means that a "packet" may comprise multiple code blocks sent in parallel within one TTI.
- Re-transmissions and first transmissions to the same user are not allowed
- 25 within the same TTI.
- The modulation, coding scheme and power level for first transmissions are chosen to maximise throughput.
- All re-transmissions are scheduled before first transmissions, thus giving them a higher priority, and no first transmissions are allowed to a MS 110
- 30 while any re-transmissions remain to be sent.

- The modulation and coding scheme of a re-transmission is the same as for the first transmission.
- The available channelisation codes are allocated in sequence, until the total available power is exhausted.

5 Figure 2 is a graph which illustrates the potential improvements using power control information in the simulated scenario, showing how the 95 percentile delay D , in seconds, for packet delivery depends on the offered load in Mbps (millions of bits per second) for a MS 110 moving at 10km/h. Results are shown for Reporting Cycles (RC) of once per 1, 10 and 100 TTIs, indicated
10 respectively by square, circular and triangular markers. The solid lines relate to the BS 100 making no use of power control information, while the dashed lines relate to the BS 100 using power control information to correct the channel quality report, as discussed above. It can clearly be seen that use of power control information provides significant improvements as the rate at which the
15 MS 110 issues reports is reduced. In particular, there is virtually no drop in system throughput at saturation when power control information is used, compared with a significant drop when it is not used.

 Figure 3 is a similar graph to Figure 2, but for a MS 110 moving at 120km/h. At such speeds the channel characterisation information is out of
20 date when the packet is transmitted, and consequently the system saturates at a significantly lower throughput than at lower speeds. The use of power control information still provides some improvement, but rather less than for a slowly moving MS, particularly for higher offered loads.

 An improved method of addressing the effect of a moving MS 110 is
25 provided, in a system made in accordance with the present invention, by averaging the reported channel characteristics. Figure 4 is a graph similar to Figures 2 and 3, for a mobile moving at 120km/h. However, the dashed lines now relate to the performance when the channel quality reports are averaged over 15 time slots preceding the report. It can be seen that the delays are
30 significantly reduced compared to the use of power control information, even with very infrequent measurement reports (such as once per 100 TTIs). This

could enable the frequency of measurement reports to be reduced without compromising system throughput, thereby reducing uplink interference.

Figure 5 is a graph showing the delay D for a range of offered loads O for a MS 110 moving at 120km/h, a reporting cycle of once per 100 TTIs and averaging periods (AV) of 1, 3, 15 and 150 slots (indicated respectively by square, circular, triangular and diamond markers). It can be seen that each increase in the averaging period, up to 150 slots, reduces the delay. Even an average over a relatively short period, such as 3 slots, provides a significant improvement over no averaging and also over the use of power control information. The two techniques can also be used together, providing further benefits.

Even at low speeds, where the invention is unnecessary due to the effectiveness of using information from the closed-loop power control, some averaging may be used without significant effects. For example, simulations of a MS 110 moving at 3km/h showed no significant degradation when a 3 slot averaging was used.

The averaging of channel characteristics may either be performed by the MS 110 or the BS 100. If performed by the BS 100, it could be by the averaging of individual channel reports transmitted once per TTI by the MS 110. However, it is advantageous to have the averaging performed by the MS 110 as this enables the frequency with which the reports are transmitted to be reduced, thereby reducing uplink interference. The averaging period could be fixed, but in a preferred embodiment it is signalled by the BS 100 to the MS 110. The BS 100 could either signal the times, relative to the transmission time of the channel report, at which measurements should begin and end or signal the duration of the channel measurement period. Optionally, the delay between the end of the measurement period and the transmission of the report could be signalled. The duration of the measurement period could be signalled in any convenient manner. The MS 110 could make measurements continuously during this period, or preferably take a number of sample measurements which are then averaged. In this latter case, the signalled duration could indicate the number of measurements to be taken, with the

length of and time between the measurements being either predetermined or signalled.

The BS 100 can make use of its knowledge of the averaging period, for example to predict the reliability of the received channel reports. This could be used as an input to the scheduling algorithm, for example weighting channel reports by their determined reliability.

In a further improvement, the averaging period is made dependent on the speed with which the MS 110 is moving (which the BS 100 and/or MS 110 can determine from a range of known methods, for example Doppler fading rate, rate of change of SIR, etc). Typically the effect of this would be to increase the averaging period as the speed of the MS 110 increased. The dependency of averaging period on MS speed could be signalled by the BS 100 or could be a predetermined parameter. The MS could, if required, include an indication of its speed in a channel report.

There may be a range of other reasons for changing the averaging period. For example, it could be changed when the MS 110 begins or ends soft handover, or when the size of the active set is changed. In systems where the effective power control rate may be altered, then a change in averaging period may be desirable at the same time. In this case, signalling of a change of power control rate could be used to signal a change in averaging period, thereby avoiding extra signalling.

Figure 6 is a flow chart illustrating one way in which a system having speed measurement capability could operate. It starts, at step 602, with a MS 110 opening a HSDPA connection with a BS 100. At step 604 the speed V of the MS 110 is determined, either by the MS or the BS. At step 606 a test is made to determine whether V is outside the range appropriate for the currently selected averaging period. If it is not (N) the system returns to step 604. If it is, the length of time over which averaging should take place is reset, either by the MS 110 or by signalling from the BS 100, after which the system returns to step 604.

As an alternative to the averaging period being determined by the BS 100, it could be determined by the MS 110, based on its speed and/or on other

channel characteristics. The selected period could then be signalled to the BS 100 if required, to enable the BS 100 to make use of its knowledge of this period, as indicated above.

5 The description above related to the BS 100 performing a variety of roles relating to the present invention. In practice these tasks may be the responsibility of a variety of parts of the fixed infrastructure, for example in a "Node-B", which is the part of the fixed infrastructure directly interfacing with a MS 110, or at a higher level in the Radio Network Controller (RNC). In this specification, the use of the term "base station" or "primary station" is
10 therefore to be understood to include the parts of the network fixed infrastructure involved in an embodiment of the present invention.

From reading the present disclosure, other modifications will be apparent to persons skilled in the art. Such modifications may involve other features which are already known in the design, manufacture and use of
15 communication systems and component parts thereof, and which may be used instead of or in addition to features already described herein.

CLAIMS

1. A communication system having a downlink data channel for the transmission of data packets from a primary station to a secondary station and
5 uplink and downlink control channels for the transmission of control information between the primary and secondary stations, wherein the secondary station has means for measuring at least one characteristic of the data channel and for transmission of reports relating to one or more of the measured channel characteristics to the primary station on the uplink control channel, wherein the
10 primary station has time signalling means for instructing the secondary station, via the downlink control channel, of the length of time during which channel measurements used to generate each report should be made and wherein the primary station has means for determining at least one operational parameter of the data channel depending on the reports.

15

2. A primary station for use in a communication system having a downlink data channel for the transmission of data packets from the primary station to a secondary station and uplink and downlink control channels for the transmission of control information between the primary and secondary
20 stations, wherein means are provided for receiving on the uplink control channel reports relating to one or more measured channel characteristics of the data channel from the secondary station, time signalling means are provided for instructing the secondary station, via the downlink control channel, of the length of time during which channel measurements used to
25 generate each report should be made and means are provided for determining at least one operational parameter of the data channel depending on the reports.

3. A primary station as claimed in claim 2, characterised in that the
30 time signalling means signals the number of measurements to be made to generate each report.

4. A primary station as claimed in claim 2 or 3, characterised in that the time signalling means signals the interval between each of the measurements to be made to generate each report.

5. A primary station as claimed in claim 2, characterised in that means are provided for determining the speed of the secondary station and in that the time signalling means is responsive to the determined speed to vary the signalled length of time.

6. A secondary station for use in a communication system having a downlink data channel for the transmission of data packets from a primary station to a secondary station and uplink and downlink control channels for the transmission of control information between the primary and secondary stations, wherein means are provided for measuring at least one characteristic of the data channel, for transmission of reports relating to one or more of the measured channel characteristics to the primary station on the uplink control channel, and for receiving, via the downlink control channel, instructions of the length of time during which channel measurements used to generate each report should be made.

20

7. A system as claimed in claim 6, characterised in that a measured characteristic is one of: bit error rate; signal to noise ratio; signal to interference ratio.

25

8. A system as claimed in claim 6 or 7, characterised in that the primary and secondary stations each comprise a plurality of antennas and in that measured characteristics are provided for a plurality of combinations of paths between antennas.

30

9. A secondary station for use in a communication system having a downlink data channel for the transmission of data packets from a primary station to a secondary station and uplink and downlink control channels for the

15

PHGB 020104

transmission of control information between the primary and secondary stations, wherein means are provided for measuring at least one characteristic of the data channel, for transmission of reports relating to one or more of the measured channel characteristics to the primary station on the uplink control channel, and for determining the length of time during which channel measurements used to generate each report should be made.

10. A secondary station as claimed in claim 9, characterised in that means are provided for signalling to the primary station on the uplink control channel the length of time for which channel measurements are made.

11. A method of operating a communication system having a downlink data channel for the transmission of data packets from a primary station to a secondary station and uplink and downlink control channels for the transmission of control information between the primary and secondary stations, wherein the secondary station measures at least one characteristic of the data channel and transmits reports relating to one or more of the measured channel characteristics to the primary station on the uplink control channel, wherein the primary station instructs the secondary station, via the downlink control channel, of the length of time during which channel measurements used to generate each report should be made and wherein the primary station determines at least one operational parameter of the data channel depending on the reports.

12. A communication system constructed and arranged to operate substantially as hereinbefore described with reference to and as shown in the accompanying drawings.

13. A primary station constructed and arranged to operate substantially as hereinbefore described with reference to and as shown in the accompanying drawings.

16

PHGB 020104

14. A secondary station constructed and arranged to operate substantially as hereinbefore described with reference to and as shown in the accompanying drawings.

5 15. A method of operating a communication system substantially as hereinbefore described with reference to and as shown in the accompanying drawings.

ABSTRACT

COMMUNICATION SYSTEM

5 A communication system comprises a downlink data channel for the transmission of data packets from a primary station to a secondary station and uplink and downlink control channels. The secondary station measures one or more characteristics of the data channel and issues a report to the primary station, which determines an operational parameter of the data channel in response to the report. The secondary station determines average channel
10 characteristics over a measurement period. The length of the measurement period may be signalled by the primary station or determined directly by the secondary station. In one embodiment the selected period depends on the speed (V) of the secondary station. This is determined (604) by either station
15 and tested to determine (606) whether it is outside the range for the current measurement period: if it is the period is reset (608).

(Figure 6)

1/3




FIG. 1




FIG. 2

2/3




FIG. 3




FIG. 4

3/3




FIG. 5




FIG. 6

**This Page is Inserted by IFW Indexing and Scanning
Operations and is not part of the Official Record**

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☐ BLACK BORDERS
- ☐ IMAGE CUT OFF AT TOP, BOTTOM OR SIDES
- ☐ FADED TEXT OR DRAWING
- ☒ BLURRED OR ILLEGIBLE TEXT OR DRAWING
- ☐ SKEWED/SLANTED IMAGES
- ☐ COLOR OR BLACK AND WHITE PHOTOGRAPHS
- ☐ GRAY SCALE DOCUMENTS
- ☒ LINES OR MARKS ON ORIGINAL DOCUMENT
- ☐ REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY
- ☐ OTHER: _____

IMAGES ARE BEST AVAILABLE COPY.

As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.